

# CAP-1 Specifications

CAP-1 SDI to USB 3.0 Capture Box	
Input	1x HD/3G-SDI
Output	1x USB 3.0 (Micro B) 1x SDI loopthrough
Input Video Bandwidth	150MHz (pixel clock rate)
Output Video Bandwidth	Up to 350Mbps (USB)
Supported Input /Output Video Formats	1920 x 1080p 60/59.94/50/30/29.97/25/24/23.976 1920 x 1080i 60/59.94/50 (de-interlaced out) 1280 x 720p 60/59.94/50
Audio Input	SDI Embedded Audio & 3.5 mm stereo in
Audio Format	2-Channel, 16-bit PCM
Recording Video Format	YUY2 (USB3.0), MJPG (USB2.0/3.0)
Firmware Update	Via USB Port
Software Compatibility	Windows: Amcap, Google Plus Hangouts, OBS (Open Broadcast Software), Skype, VLC, Xsplit Broadcaster, Zoom.us Linux: VLC, OBS Mac OS X: OBS, Quicktime player, VLC, Facetime
Supported OS	Windows® 7(SP1) / Windows 10 / Windows 8.1 / Windows 7 (x86, x64), OS X (10.10 or above), Linux Ubuntu 14.04
Power Supply	Via USB
Power Consumption	3W
Operation Temperature	0~40°C
Storage Temperature	-20~60°C
Humidity	20~90% RH

Minimum System Requirement	<ul style="list-style-type: none"><li>• Windows® 7(SP1) / Windows 10 / Windows 8.1 / Windows 7 (x86, x64) Note: The driver is required for Windows 7 OS</li><li>• OS X (10.10 or above)</li><li>• Linux Ubuntu 14.04</li><li>• PC: Intel® Core™ i5-4440 3.10GHz + NVIDIA® GeForce® GTX 660 or higher</li><li>• Laptop: Intel® Core i7-4810MQ + NVIDIA GeForce GTX 870M or higher 4GB RAM or higher</li></ul>
Dimension (LxDxH)	121 x 68 x 23 mm
What's in the Box	1 x CAP-1 1 x Thank You Card 1 x USB 3.0 Cable