

## Safety Cabinet / Charging Cabinet – HiSafe – S10-10 for Laptops, iPads / Tablets (Safety Class SSF 3492)



**Safety Cabinet/Charging Cabinet - HiSafe** - for protection and charging of up to 10 Laptops / 20 iPads/Tablets/Mini-Laptops.  
Classified, Tested and Approved for maximum safety.

Partno: **S10-10 Safety Cabinet/Charging Cabinet - HiSafe** (For protection and charging of up to **10 Laptops / 20 iPads/Tablets**)

If the partnumber ends with the letter "K" (eg. S10-10K), the cabinet is delivered with Code Lock as standard.

External dimensions cabinet: Height: 1000 Width: 575 Depth: 500 (mm)

Internal measurement cabinet: Height: 992 Width: 450 Depth: 440 (mm)

Shelf depth: 440 mm (Maximum depth Laptop/Tablet)

Shelf Width: 450 mm (Total maximum width Laptops/Tablets)

Space between shelves at 20 shelves: 75mm (Adjustable in increments of 20mm).

Interior: 10 shelves (1 Laptop or 2 iPads/Tablets/Mini-Laptops on each shelf).

### Other information

Ventilation: Mechanical ventilation for charging (Well-sized hole image in cabinet for charging).

As an option, the cabinet can be equipped with a thermostatically controlled fan (628-333), which enables the Laptops / Tablets to be in operation if there is a need to update these at night. (fan is not required for charging only). If necessary for a network switch, this can be mounted on any shelf in the cabinet.

Charging: 1 socketstrip (220v) with 10 sockets in each strip. Additional socket strip is available as an option if more sockets are needed (635). Number of socket strips as standard:

S10-10 (1pcs). An optional 3-Phase adapter is also available.

Smart Charging via App/Wifi. Easy scheduling of charging in groups. Minimizes load of the electrical system.

Keylock / Code-Lock: Delivered as standard with key lock and 2 keys. Code lock is available as an option (see option for more info).

Installation: Freestanding or bolting in floor or wall.

Weight: 167 (kg)

Safety class: **SSF 3492**

Color: White

### Optional:

Partno. **S-CODE** Code-Lock (Easy to use and easily programmable code lock with Master code and up to 10 user codes (Good choice to eliminate key-management).

Partno. **S-Key** Key - Cabinet order (2 keys are included as standard. If many keys are needed, code lock is recommended).

Partno. **ES-Key** Key - Reorder (If reorder, this option is selected).

Partno. **637** 3-Phase adapter (3pcs standard 220v socket to 1pc 3-phase socket "16A-416-Schuko-Red". Length: 3m)

Partno. **628-333** Thermostatic fan (Fan is not required for charging only)


Partno. **635** Additional Socket Strip (10-Socket)

Partno. **6402** Shelf Divider (1st)

Partno. **640** Shelf Divider (5-pack)

Partno. **6899-16** Charge-Sync-Unit for 16 iPads/Tablets (USB)

Partno. **6899-6** Charging Station USB-6-Port (iPads/Tablets)



### **Shelf divider** (Partno. 6402/640)

As an option, there are shelf dividers for storage of Laptop / Tablet on top. The divider is mounted steplessly in any width.



6899-16 Charge/Sync-Unit (Optional)



6899-6 Charging Station USB-6-Port (Optional)